


Product Specifications



Cyclic - Deep Cycle - Starting - Stand By - Marine - Back up Power

- **High Performance Genuine AGM Battery** - Completely sealed and Non-spillable Dry Cell. Can be used on any angle or even upside down.
- **Longer Service Life** - Up to 30% more cycle life than other leading brands.
- **State-Of-The-Art Thermal Management System** - Keeps battery cool during charging & general use making it better suited to hotter climates (like Australia's top end) and under bonnet use. Also extends battery life
- **Extreme Vibration Resistant**
- **Special Cycle Alloy (CBC Series)** - Extends the life of the battery, reduces self discharging and improves true deep discharge performance
- **Absorbed Glass Matt Separators (AGM)**
- **Extra Thick Plates** - For increased capacity
- **Superior Design & Quality** - Manufactured to Quality Assurance Standard ISO 9001 are CE Certified
- **Manufactured to comply with AS 4029.2-2000**
- **Extended 3 Years Warranty** - When used as back-up power supply for Fire Pumps and other appropriate Fire Systems
- **CBC Series Rated for Under Bonnet Use** - Can also be used as a vehicle Starting battery or Dual Purpose Starting/Deep Cycle/Marine battery. Warranty covers under bonnet use
- **Flame Retardant ABS Plastic** - Making it the safest available in Australia
- **When Failure is not an Option** - Use only Fusion AGM Batteries

PART NUMBER	CB6V4.5AH
BATTERY TYPE	AGM VRLA - Standard Use
VOLTAGE	6 Volts
AH (20hr):	4.5
DIMENSIONS	
Length	70mm
Width	47mm
Height	100mm
Terminal Height	106mm
TERMINAL TYPE	T1
	
TERMINAL ASSEMBLY	
OTHER FEATURES	
WEIGHT	0.81 KG
REGULAR CHARGE	0.4 Amps
MAX CHARGE	1.2 Amps
SEPARATOR TYPE	Absorbed Glass Mat
USAGE	Stand By
WARRANTY	Private use 12 Months

MAINTENANCE REQUIREMENTS:

Despite this being labeled as a "Maintenance Free" battery there is still some minimal maintenance requirements. The battery industry generally uses the term "Maintenance Free" when you are not required or cannot add acid to the battery because it is sealed. Like all Maintenance Free Batteries (no matter what brand), it is essential to periodically service the battery to ensure maximum life. As a general rule of thumb this should be done each time your vehicle / equipment is serviced by your mechanic / technician.

Service requirement include:

- o Check electrical connections to ensure they are clean & tight
- o Do not overcharge battery. Maximum recharging voltage is 14.6 Volts.
- o Keep battery clean & dry. Use only bicarbonate of soda & water to clean. Rinse afterwards with clean water.
- o Ensure that unused battery is charged every 3 months or when voltage is below 12.6 Volts.
- o Failure to follow these instructions will void warranty.

SAFETY PRECAUTIONS

Lead-acid batteries generate explosive gases.

Keep sparks, flames and lighted cigarettes away from battery. Keep metal objects away from terminals. When charging or using in enclosed spaces, provide ventilation. The battery contains sulphuric acid.

Should acid spill from the battery, Avoid contact with skin, eyes, or clothing. In event of accident flush with water and call doctor immediately.

Looking for another battery? [Click here to search again.](#)



CBC6V6AH AGM Cyclic VRLA Battery